



MODEL: 6000HM
6.0kVA PETROL GENERATING SET

OUTPUT:	6.0kVA / 4.8kW , 50Hz, Single Phase
CONTROL PANEL:	Alternator top mounted metal control box comprising 1x16a 115v, 1x32a 240v, 2x16a 230v BS4343 socket outlets, reset button circuit breakers and voltage selector switch
ENGINE:	Honda GX340 recoil start, single cylinder air cooled petrol engine with low oil level shutdown fitted with fuel tank and exhaust silencer
ALTERNATOR:	Heavy Duty Markon Brushless maintenance free alternator, single bearing
FUEL TANK:	6.5 Litre fuel tank giving approx 3 hours operation at 75% load
FRAME:	1" heavy duty tubular steel wrap around frame with anti vibration mounts
NOISE LEVEL:	72dBA @ 7mtr
DIMENSIONS:	L690mm x W480mm x H540mm
WEIGHT:	68kg (dry)
OPTIONS:	Single voltage

DATE: June 2010